# Juniper SRX320 Setup Guide (Basic Network)

This guide will help you configure your Juniper SRX320 router with the following features:

- **Three VLANs**: Home, Guest, and IoT
- **Firewall Rules**: Optimized for streaming and gaming
- **Traffic Prioritization**: Using Quality of Service (QoS)

# Prerequisites

1. **Juniper SRX320**: Ensure your SRX320 is powered on and connected to your network.
2. **J-Web Interface**: Access the router through a web browser at `http://<SRX320-IP>`.
3. **Basic Network Setup**: Have an existing internet connection and basic understanding of network configurations.

# Step-by-Step Setup

## Step 1: Access Juniper SRX320

1. **Open a web browser** and navigate to the SRX320's IP address.
2. **Log in** using the default credentials or your configured admin username and password.

## Step 2: Configure VLANs

1. **Navigate to**: `Network > Interfaces`.
2. **Create VLANs** for Home, Guest, and IoT.

#### Home VLAN

- **VLAN ID**: 10
- **Interface**: `ge-0/0/1.10`
- **IP Address**: `192.168.10.1/24`

#### Guest VLAN

- **VLAN ID**: 20

- **Interface**: `ge-0/0/1.20`
- **IP Address**: `192.168.20.1/24`

#### IoT VLAN

- **VLAN ID**: 30
- **Interface**: `ge-0/0/1.30`
- **IP Address**: `192.168.30.1/24`

## Step 3: Configure DHCP for Each VLAN

1. **Navigate to**: `Network > DHCP Server`.
2. **Configure DHCP** for each VLAN.

#### Home VLAN DHCP

- **Interface**: `ge-0/0/1.10`
- **Pool**: `192.168.10.10 to 192.168.10.100`

#### Guest VLAN DHCP

- **Interface**: `ge-0/0/1.20`
- **Pool**: `192.168.20.10 to 192.168.20.100`

#### IoT VLAN DHCP

- **Interface**: `ge-0/0/1.30`
- **Pool**: `192.168.30.10 to 192.168.30.100`

## Step 4: Configure Security Zones

1. **Navigate to**: `Security > Security Zones`.
2. **Create security zones** for each VLAN.

#### Home Zone

- **Zone Name**: home
- **Interfaces**: Add `ge-0/0/1.10`

#### Guest Zone

- **Zone Name**: guest
- **Interfaces**: Add `ge-0/0/1.20`

#### IoT Zone

- **Zone Name**: iot

- **Interfaces**: Add `ge-0/0/1.30`

# Step 5: Configure Firewall Policies

1. **Navigate to**: `Security > Policies`.
2. **Create policies** to manage traffic between zones.

#### Allow Traffic from Home to Internet

- **Source Zone**: home
- **Destination Zone**: untrust
- **Policy**: Allow

#### Allow Traffic from Guest to Internet

- **Source Zone**: guest
- **Destination Zone**: untrust
- **Policy**: Allow

#### Allow Traffic from IoT to Internet

- **Source Zone**: iot
- **Destination Zone**: untrust
- **Policy**: Allow

#### Deny Traffic Between VLANs

- **Source Zone**: home
- **Destination Zone**: guest, iot
- **Policy**: Deny
- **Source Zone**: guest
- **Destination Zone**: home, iot
- **Policy**: Deny
- **Source Zone**: iot
- **Destination Zone**: home, guest
- **Policy**: Deny

# Step 6: Configure Traffic Prioritization (QoS)

1. **Navigate to**: `Network > Quality of Service`.
2. **Create QoS profiles** to prioritize gaming and streaming traffic.

#### Create Classifiers for Gaming and Streaming

- **Classifier Name**: gaming
  - **DSCP**: 46 (EF for low latency)
  - **Application**: Match traffic to gaming servers

- **Classifier Name**: streaming
  - **DSCP**: 34 (AF41 for streaming)
  - **Application**: Match traffic to streaming services

**Apply Classifiers to Interfaces**

- Apply the classifiers to the interfaces connected to your gaming and streaming devices.

## Step 7: Apply and Test Configuration

1. **Review all configurations** and apply changes.
2. **Test the network**:
   - Verify that devices on each VLAN receive the correct IP addresses.
   - Test internet connectivity for devices on each VLAN.
   - Ensure that gaming and streaming traffic is prioritized as expected.

# Additional Tips

- **Secure Access**: Change the default admin password and restrict management access to trusted IPs.
- **Regular Backups**: Backup your configuration regularly to prevent data loss.
- **Firmware Updates**: Keep the SRX320 firmware updated for security and performance enhancements.

---

Revision #1
Created 9 August 2024 12:57:01 by Jarryd
Updated 9 August 2024 13:40:35 by Jarryd